

---



# Selecting Supported RFID Tag Types

---

## Read This First

---

Printronix RFID SL5000 MP and MP2 printers support a number of RFID protocols and antenna configurations.

To view a complete list of tag types supported by Printronix RFID SL5000 printers, and a list of Certified RFID Smart Labels available from Printronix:

1. Go to [www.primtronix.com](http://www.primtronix.com) and select your Country/Language of choice.
2. Under SOLUTION OFFERINGS, click **RFID Printers**.
3. Under **RFID Smart Labels**, click **View Series**.
  - a. For a complete list of supported RFID tag types, click **Supported RFID Tags**.
  - b. For a list of Certified RFID Smart Labels available from Printronix, click **Certified RFID Labels**.

These web pages will be updated regularly to include newly supported RFID tag types and newly Certified RFID Smart Labels available from Printronix.

To configure your printer to use an RFID tag type, see “Selecting RFID Tag Types” below.

---

## Selecting RFID Tag Types

---

For additional information on menu operation, refer to the *Quick Setup Guide*, *User's Manual*, and *RFID Labeling Reference Manual*.

To select an RFID tag type:

1. Press the ☰ key on the printer control panel to take the printer offline and into Menu mode.
2. Press ↓ and ↵ together until ENTER SWITCH / UNLOCKED displays.
3. Press ☰ until RFID CONTROL displays.
4. Press ↓ until Tag Type displays.

**NOTE:** If Tag Type does not display, set Admin User to Enable (in the PRINTER CONTROL menu).

- 
5. Press ← or → until the desired tag type displays. If the desired tag type does not display, use the substitution tables below to select the compatible tag type.

**Table 1. MP RFID**

<b>Newly Supported Tag Type</b>	<b>Compatible Tag Type</b>
Alien Gen2 Squiggle	EPC Gen 2 96
Avery AD-210 (aka Strip)	Alien Squig 96
Avery AD-220 (aka Runway)	EPC Gen 2 96
Omron Loop	Alien Squig 96
TI Dallas	EPC Gen 2 96

**Table 2. MP2 RFID**

<b>Newly Supported Tag Type</b>	<b>Compatible Tag Type</b>
Avery AD-210 (aka Strip)	Alien Squig 96

6. Press ↵ to select the tag type. An asterisk (\*) displays next to the selected tag type.
7. If you want this selection to remain permanent, save the configuration and set the configuration to be the Power-Up Config. (in the QUICK SETUP or CONFIG. CONTROL menu). Refer to the *Quick Setup Guide* or the *User's Manual*.